




DVR Specification

03 Series 5.0MP 5 in 1 Hybrid DVR

Model		VP-HD0803-TE		VP-HD1603-TE	
Picture					
Operation System		Embedded Linux			
Video Audio Input	Video Input	4ch		8ch	
		CVBS、TVI、AHD、CVI Self-adapt、IP Camera Connection			
		Support TVI/AHD/CVI UTC			
		BNC Interface (1.0Vp-p,75ohms)			
	5MP/4MP/3MP/1080P/720P/WD1/D1				
Video Audio Output	Network Video Input	32Mbps		64Mbps	
	Audio Input	Up to 2048*1536@30FPS			
	Voice Talk	1ch, RCA Interface(2Vpp,1Kohms)			
	CVBS Output	1ch Voice Talk			
Encode	VGA	1ch,BNC Interface (1.0Vp-p,75ohms)			
	HDMI	1ch,1920x1080,1280x1024,1366x768,1280x720,1024x768 Selectable			
	Audio Output	Ver. 1.3a			
	Video Encode	Ver. 1.4a			
	Resolution	1920x1080,1280x1024,1366x768,1280x720,1024x768 Selectable			
Decode	Video Frame Rate	3840x2160、1920x1080,1280x1024,1366x768,1280x720,1024x768 Selectable			
	Bitrate Control	1ch, RCA Interface(Line out,2Vpp,300ohms)			
	Video Bitrate	5MP、4MP、3MP、1080P、720P、WD1、D1			
	Stream Type	H.264 High Profile@Level4.2			
	Audio Encode	Main Stream: 5MP、4MP、3MP、1080P、720P、WD1、D1 Selectable			
	Audio Bitrate	Sub Stream:			
	Double Stream	D1: D1@25fps(P)/30fps(N)			
	Video Decode Standard	CIF: CIF@25fps(P)/30fps(N)			
	Playback	CBR/VBR Selectable			
	The Highest Resolution	48Kbps-8192Kbps			
Intelligent Function	Motion Detection	Composite Stream / Video Stream			
		G.711A			
		64Kbps			
		Support, The sub stream up to D1@25fps(P)/30fps(N)			
	Face Detection	H.264(High Profile@Level4.2)			
Other	Masking	4 Channel Synchronous Playback		8 Channel Synchronous Playback	
		2ch 1080P@30FPS or 2ch 5MP@10FPS		4ch 1080P@30FPS or 4ch 5MP@10FPS	
		1CH Face Detection or 4 CH Intrusion Detection		2CH Face Detection or 8 CH Intrusion Detection	
		1080P Resolution MAX		Two-way Voice Talk	
	Snapshot	Each Channel Support 396 (22x18) Detection Area; Support Multi-level Sensitivity			
HDD	SATA Port maximum	Support 4 area masking each channel			
		Support Jpeg Snapshot			
		1		2	
		No Limitation			
	Network Port	1 RJ45;10M/100M Suitable Ethernet Port		1 RJ45;10M/100M/1000M Suitable Ethernet Port	
External Interface	USB Port	2 USB2.0			
	Alarm Input	N/A		8	
	Alarm Output	N/A		4	
	Power	N/A		N/A	
	Structure	Support, Half-duplex			
Electrical Performance	RS-485	370x305x115mm		405x335x120mm	
	Packing Size	320x246x48mm		360x262x48mm	
	Installation	Desktop Installation			
	Power Supply	DC +12V 2A		DC +12V 4A	
	Operation	DC +12V 4A		DC +12V 4A	
Power	Power	0℃--+55℃		10%~90%	
		7w(Not Include HDD)		11w(Not Include HDD)	
		20w (Not Include HDD)		20w (Not Include HDD)	






FASTEST P2P

VSS is specially designed for low bandwidth network like streamyx, private ip (maxis, time, telekom, 3G/4G sim card, YES & P1. Asimple qr code scan in order in to view in ypur mobile. No port forwarding, no configuration. Brand X,Y,Z P2P slow, so that they need to use DDNS which you need to pay and bare the cost, worse is annually fees in increasingtime by time, Who is going to absord this extra cost? Customer or You?

FACE DETECTION

DVR will track faces and display the photo on the tv screen, user can playback instantly by searching faces. Phsycologically the thieves will feel uncomfortable as the tv screen is displaying their and monitoring them closely.




PERIMETER INTRUSION DETECTION

The Search by time line and alarm events. Take snapshots alarm upon line-crossing or area intrusion. Snapshots can upload to dropbox and google drive automatically.

VSS MEDIA CENTRE

Backup ebents through phone and share it to others immediately without doing it in PC. It saved face detection and perimeter event in the phone.



VSS DEVICES IN CLOUD

Store all your DVR account or divices through the phone, when user lost/change phone,it just need to log in user account and it able to view all hundreds of dvr devices, instead of key in 1by 1.

VSS TROUBLE FREE FROM HACKED

Most of the China DVR is under ddos attack due to the backdoor unpatched as result :

- 1 - The TV Display will become blank or black coulour
- 2 - Hacked word will appear on every channel on tv display
- 3 - IP Address reset default by itself, Password changed.



VSS HAS 2 LAYER OF PASSWORD

One password is for DVR, another password is for Internet. User Forgotten password on phone, user can retrieve password from the dvr itself, unlike other DVR, need to bring back DVR to distributors for passwiord recovery.

ALL CHANNEL PLAYBACK

All able to Playback All Channel on DVR.






NETWORK FAIL NOTIFICATION

It will pop out event display on the tv or buzzer beep sound to alert user.

VIDEO OUTPUT HDMI, VGA, BNC

VSS comes with HDMI, VGA, Bnc Output.
Unlike others only VGA and HDMI.



PUSH NOTIFICATION

Immediate push notification event sent to user, for both apple iphone and android.

GOOGLE DRIVE BACKUP

In the event of DVC is being stolen, you can have alternative source to get the recorded data picture.

